

Стабилизаторы напряжения POMING

PM-1005, PM-101, PM-101.5, PM-102, PM-103, PM-105, PM-110, PM-110K, PM-115K, PM-120K, PM-130K

Технические характеристики

Архангельск (8182)63-90-72	Ижевск (3412)26-03-58	Магнитогорск (3519)55-03-13	Пермь (342)205-81-47	Сургут (3462)77-98-35
Астана (7172)727-132	Иркутск (395)279-98-46	Москва (495)268-04-70	Ростов-на-Дону (863)308-18-15	Тверь (4822)63-31-35
Астрахань (8512)99-46-04	Казань (843)206-01-48	Мурманск (8152)59-64-93	Рязань (4912)46-61-64	Томск (3822)98-41-53
Барнаул (3852)73-04-60	Калининград (4012)72-03-81	Набережные Челны (8552)20-53-41	Самара (846)206-03-16	Тула (4872)74-02-29
Белгород (4722)40-23-64	Калуга (4842)92-23-67	Нижний Новгород (831)429-08-12	Санкт-Петербург (812)309-46-40	Тюмень (3452)66-21-18
Брянск (4832)59-03-52	Кемерово (3842)65-04-62	Новокузнецк (3843)20-46-81	Саратов (845)249-38-78	Ульяновск (8422)24-23-59
Владивосток (423)249-28-31	Киров (8332)68-02-04	Новосибирск (383)227-86-73	Севастополь (8692)22-31-93	Уфа (347)229-48-12
Волгоград (844)278-03-48	Краснодар (861)203-40-90	Омск (3812)21-46-40	Симферополь (3652)67-13-56	Хабаровск (4212)92-98-04
Вологда (8172)26-41-59	Красноярск (391)204-63-61	Орел (4862)44-53-42	Смоленск (4812)29-41-54	Челябинск (351)202-03-61
Воронеж (473)204-51-73	Курск (4712)77-13-04	Оренбург (3532)37-68-04	Сочи (862)225-72-31	Череповец (8202)49-02-64
Екатеринбург (343)384-55-89	Липецк (4742)52-20-81	Пенза (8412)22-31-16	Ставрополь (8652)20-65-13	Ярославль (4852)69-52-93
Иваново (4932)77-34-06	Киргизия (996)312-96-26-47	Россия (495)268-04-70	Казахстан (772)734-952-31	

PM series single-phase high-precision voltage regulator

PM series single-phase high-precision automatic AC voltage regulator consists of contact auto-connected voltage regulator, servo motor, automatic control circuit, etc.



Strengths:

When the power grid voltage is unstable or the load changes, the automatic sampling control circuit sends out The signal drives the servo motor to adjust the position of the carbon brush of the auto-regulator, so that the output voltage is adjusted to the rated value and reaches a stable state. This product has the characteristics of undistorted waveform, reliable performance, long-term operation, etc., with delay, over Pressure, undervoltage protection, etc. It can be widely used in any place where electricity is needed for stable voltage, and it is an ideal regulated power supply to ensure normal operation of your electrical equipment.

Application

This series regulator is suitable for small and medium-sized electromechanical equipment, production lines, construction machinery, microcomputers, rust, air conditioners, refrigerators, stereos, televisions, and other devices in the fields of industry, agriculture, medical care, radio and television, communications, communications, scientific research, and culture. Home appliances, lighting and other places that need to be regulated.

Technical parameters

Input voltage	150V-250V
Output voltage	220V/110V(0.5kVA-3kVA) 220V(5kVA-30kVA)
Voltage regulation accuracy	Phase voltage 220V \pm 3% 110V \pm 6%
frequency	50Hz/60Hz
Overvoltage protection	246V \pm 4%
Adjust the time	<1 second (when input voltage changes by 10%)
Ambient temperature	-10°C~+40°C
Temperature rise	<60°C
Waveform distortion	No additional waveform distortion
Load power factor	0.8
Dielectric strength	1500V/1min
Insulation resistance	>2M Ω

Outer size/Packaging

Model/Specifications	Size (cm)	Package (cm)	Package Quantity (piece)	Gross Weight (kg)
PM-1005	19 × 17 × 13.5	44 × 24.5 × 35	4	15
PM-101	22 × 20.2 × 16	49 × 28.5 × 40	4	20
PM-101.5	22 × 20.2 × 16	49 × 28.5 × 40	4	26
PM-102	24.5 × 25.8 × 19.5	60.5 × 35 × 25.5	2	17
PM-103	23.5 × 29 × 23	61.5 × 38.5 × 29	2	23
PM-105	23 × 31.5 × 27.5	39.5 × 32 × 35	1	13
PM-110 (ultra-low pressure)	31 × 34.5 × 53.5	45 × 42.5 × 62	1	33
PM-110K	31 × 34.5 × 53.5	45 × 42.5 × 62	1	36
PM-115K	28 × 38 × 77	49 × 40 × 86.5	1	52
PM-120K	32.5 × 38 × 77.5	49 × 44.5 × 88.5	1	59
PM-130K	37.5 × 41.5 × 78.5	53 × 49 × 88.5	1	74

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93