

Фильтры радиочастотные диэлектрические POMING

Технические характеристики

Архангельск (8182)63-90-72	Ижевск (3412)26-03-58	Магнитогорск (3519)55-03-13	Пермь (342)205-81-47	Сургут (3462)77-98-35
Астана (7172)727-132	Иркутск (395)279-98-46	Москва (495)268-04-70	Ростов-на-Дону (863)308-18-15	Тверь (4822)63-31-35
Астрахань (8512)99-46-04	Казань (843)206-01-48	Мурманск (8152)59-64-93	Рязань (4912)46-61-64	Томск (3822)98-41-53
Барнаул (3852)73-04-60	Калининград (4012)72-03-81	Набережные Челны (8552)20-53-41	Самара (846)206-03-16	Тула (4872)74-02-29
Белгород (4722)40-23-64	Калуга (4842)92-23-67	Нижний Новгород (831)429-08-12	Санкт-Петербург (812)309-46-40	Тюмень (3452)66-21-18
Брянск (4832)59-03-52	Кемерово (3842)65-04-62	Новокузнецк (3843)20-46-81	Саратов (845)249-38-78	Ульяновск (8422)24-23-59
Владивосток (423)249-28-31	Киров (8332)68-02-04	Новосибирск (383)227-86-73	Севастополь (8692)22-31-93	Уфа (347)229-48-12
Волгоград (844)278-03-48	Краснодар (861)203-40-90	Омск (3812)21-46-40	Симферополь (3652)67-13-56	Хабаровск (4212)92-98-04
Вологда (8172)26-41-59	Красноярск (391)204-63-61	Орел (4862)44-53-42	Смоленск (4812)29-41-54	Челябинск (351)202-03-61
Воронеж (473)204-51-73	Курск (4712)77-13-04	Оренбург (3532)37-68-04	Сочи (862)225-72-31	Череповец (8202)49-02-64
Екатеринбург (343)384-55-89	Липецк (4742)52-20-81	Пенза (8412)22-31-16	Ставрополь (8652)20-65-13	Ярославль (4852)69-52-93
Иваново (4932)77-34-06	Киргизия (996)312-96-26-47	Россия (495)268-04-70	Казахстан (772)734-952-31	

Dielectric Filter

Features

High dielectric constant, small size

Low insertion loss

High Q

SMT

Frequency: 0.4GHz ~ 6GHz

Power: 1W ~ 30W

Customize



Typical Applications

Microwave telecommunication

Radar

Navigation

Technical Parameters

Part	Center Frequency (MHz)	Bandwidth (MHz)	Insertion Loss(dB)	Ripple (dB)	VSWR	Stopband Suppression (*dB@*MHz)	Dimension W*H*L (mm)	Typical Application
JML5800A	5800	200	2.50	1.00	2.00	25dB@5400 23dB@6200	4.4*4.5*2	Customize
JML5250	5250	2	3	1	1.5	50dB@5750 50dB@6250	8.2*4.6*3.2	Customize
JML5825	5825	200	2.50	1.00	1.20	40dB@5425	8.2*3.85*3.0	Customize
JML6250	6250	2	3.00	1.00	1.50	50dB@5250 50dB@5750	8.2*4.9*3.2	Customize
JML1268	1268	20	1.00	0.50	1.50	37dB@1615	8.5*5.6*3.7	Customize
JML2250	2250	100	3.00	0.50	1.50	60dB@2800 50dB@1800	13*12*4.5	Customize
JML1450	1450	140	2.00	1.00	1.50	40dB@1268 40dB@2140 30dB@2638	13*12*4.5	Customize
JML842	842	103	3.00	1.00	1.50	60dB@1685 50dB@2527.5	52*24*7.5	Customize
JML830	830	10	3.50	1.00	2.00	28@fo±40	8.2*2.9*9.0	CDMA
JML875	875	10	3.50	1.00	2.00	28@fo±40	8.2*2.9*8.6	
JML827	827.5	15	2.50	0.50	1.50	55@fo±45 45@fo-88.5	13*5*12	
JML872	872.5	15	2.50	0.50	1.50	55@fo±45 45@fo-88.5	13*5*12	
JML836	836	25	3.00	1.00	1.50	55@869~894	33.4*9*16	
JML881	881.5	25	3.00	1.00	1.50	55@824~849	33.4*9*16	

JML900	900	30	3.00	0.80	1.50	45@fo±55	13*5*12.5	GSM
JML945	945	30	3.00	0.80	1.50	45@fo±55	13*5*12.5	
JML902	902.5	25	3.00	1.00	1.50	20@fo+32.5	13*5*12	
JML947	947.5	25	3.00	1.00	1.50	20@fo-32.5	13*5*12	
JML912	912	6	2.50	1.00	1.50	50@fo±100	13*5*12	
JML957	957	6	2.50	1.00	1.50	50@fo±100	13*5*12	
JML897	897	24	3.00	0.80	1.50	45@fo±30	27*9*12	
JML942	942	24	3.00	0.80	1.50	45@fo±30	27*9*12	
JML947	947	100	2.00	1.00	1.50	30@fo±100	13*6.0*12	
JML903	903.75	7.5	3.00	1.00	1.50	20@fo±23	13*6.0*12	
JML948	948.75	7.5	3.00	1.00	1.50	20@fo±23	13*6.0*12	
JML1950	1950	60	2.50	1.00	1.50	55@fo±160	14*5*8	
JML2140	2140	60	2.50	1.00	1.50	55@fo±160	14*5*8	
JML1947	1947.5	15	2.50	0.50	1.50	50@fo±80	13*5*12	
JML2137	2137.5	15	2.50	0.50	1.50	50@fo±80	13*5*12	
JML2140A	2140	140	3.00	1.00	1.50	20@fo±140	9.6*4*6	
JML2140B	2140	60	1.50	0.50	1.50	30@fo±120	10.8*4.8*7.0	
JML2605	2605	60	2.50	0.70	1.50	22@fo-120 20@fo+95	10*5.0*10	TD-SCDMA TD-LTE
JML2400	2400	200	2.00	1.00	1.50	40@fo±250	13*6*12	
JML2400	2400	400	2.00	1.00	1.60	40@fo-540	10*5*10	Customize
JML2600	2600	115	3.50	0.60	1.80	50@fo±160	22.5*6.0*9	Customize
JML2040	2040	300	3.00	1.00	1.50	55@fo±360	22*5*11	Customize
JML3230	3230	445	2.00	0.80	1.50	60@fo-600	22.5*6.0*9	Customize
JML5800B	5800	200	3.50	1.50	1.50	35@fo±250	27.5*7.5*11	Customize
JML3200	3200	20	3.50	1.00	1.80	35@fo±70	10.8*3.8*8	Customize
JML4700	4700	20	6.00	1.00	1.50	40@fo±100	10.8*3.8*6	Customize

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93