

Источники бесперебойного питания (ИБП) POMICG SK12-500, SK12-600, SK12-800, SK12-1000, SK12-1200, SK12-1500, SK12-2000

Технические характеристики

Архангельск (8182)63-90-72	Ижевск (3412)26-03-58	Магнитогорск (3519)55-03-13	Пермь (342)205-81-47	Сургут (3462)77-98-35
Астана (7172)727-132	Иркутск (395)279-98-46	Москва (495)268-04-70	Ростов-на-Дону (863)308-18-15	Тверь (4822)63-31-35
Астрахань (8512)99-46-04	Казань (843)206-01-48	Мурманск (8152)59-64-93	Рязань (4912)46-61-64	Томск (3822)98-41-53
Барнаул (3852)73-04-60	Калининград (4012)72-03-81	Набережные Челны (8552)20-53-41	Самара (846)206-03-16	Тула (4872)74-02-29
Белгород (4722)40-23-64	Калуга (4842)92-23-67	Нижний Новгород (831)429-08-12	Санкт-Петербург (812)309-46-40	Тюмень (3452)66-21-18
Брянск (4832)59-03-52	Кемерово (3842)65-04-62	Новокузнецк (3843)20-46-81	Саратов (845)249-38-78	Ульяновск (8422)24-23-59
Владивосток (423)249-28-31	Киров (8332)68-02-04	Новосибирск (383)227-86-73	Севастополь (8692)22-31-93	Уфа (347)229-48-12
Волгоград (844)278-03-48	Краснодар (861)203-40-90	Омск (3812)21-46-40	Симферополь (3652)67-13-56	Хабаровск (4212)92-98-04
Вологда (8172)26-41-59	Красноярск (391)204-63-61	Орел (4862)44-53-42	Смоленск (4812)29-41-54	Челябинск (351)202-03-61
Воронеж (473)204-51-73	Курск (4712)77-13-04	Оренбург (3532)37-68-04	Сочи (862)225-72-31	Череповец (8202)49-02-64
Екатеринбург (343)384-55-89	Липецк (4742)52-20-81	Пенза (8412)22-31-16	Ставрополь (8652)20-65-13	Ярославль (4852)69-52-93
Иваново (4932)77-34-06	Киргизия (996)312-96-26-47	Россия (495)268-04-70	Казахстан (772)734-952-31	

PMUM-SK12

Features

- Super wide input voltage range, strong ability to adapt to the environment.
- Stable output voltage (pure sine wave output), can be applied to all electrical equipment.
- LCD display with plenty content
- CPU controlled
- Fast transfer time, high efficiency
- Intelligent battery management, prolonging the service life of the battery.
- Low battery, overload short circuit, over temperature protection



Specification

Mode	SK12-500	SK12-600	SK12-800	SK12-1000	SK12-1200	SK12-1500	SK12-2000
Rated Capacity(W)	400W	480W	640W	800W	1000W	1200W	1600W
Battery	12V/24V						
AC Input	Voltage	145V ~ 275V / 85V ~ 145V					
	Frequency	45Hz ~ 65Hz					
AC Output	Voltage	110V±3% / 220V±3%(Battery mode)					
	Frequency	50/60Hz±0.5					
Output Waveform	Pure sine wave						
Total Harmonic Distortion(THD)	≤±3%						
Battery Recharge Current	10A-20A (Adjustable)						
Display	LCD						
Transfer Time	< 4ms						
Environment	Noise	≤55dB					
	Temperature	0°C ~ 40°C					
	Humidity	10% ~ 90%(no condense)					
Efficiency	≥85%						
Protection	Over-load	Overload exceeds 110%, automatic shutdown in 30 secs;					
		Overload exceeds 120%, automatic shutdown in 2 secs;					
		Under mains supply mode, it will not shutdown if overload, just keeping sound.					
	Short-circuit	Output short-circuit, automatic shutdown after keeping sound 20 secs					
	Battery	High & low voltage protection					
Reverse polarity	Reverse polarity protection (optional)						
Alarm	A	Without alarm sound if work normally under mains supply mode, when mains supply cut off, turn into battery mode, keeping sound 4 times every 30 seconds.					
	B	Keeping sound every seconds when Battery low voltage; sharp sound under machine fault.					
	C	Keeping sound every seconds under overload					
Note	* All specifications are subject to change without prior notice.						

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93