

# Кабели коаксиальные POMING JML-18004

## Технические характеристики

Архангельск (8182)63-90-72	Ижевск (3412)26-03-58	Магнитогорск (3519)55-03-13	Пермь (342)205-81-47	Сургут (3462)77-98-35
Астана (7172)727-132	Иркутск (395)279-98-46	Москва (495)268-04-70	Ростов-на-Дону (863)308-18-15	Тверь (4822)63-31-35
Астрахань (8512)99-46-04	Казань (843)206-01-48	Мурманск (8152)59-64-93	Рязань (4912)46-61-64	Томск (3822)98-41-53
Барнаул (3852)73-04-60	Калининград (4012)72-03-81	Набережные Челны (8552)20-53-41	Самара (846)206-03-16	Тула (4872)74-02-29
Белгород (4722)40-23-64	Калуга (4842)92-23-67	Нижний Новгород (831)429-08-12	Санкт-Петербург (812)309-46-40	Тюмень (3452)66-21-18
Брянск (4832)59-03-52	Кемерово (3842)65-04-62	Новокузнецк (3843)20-46-81	Саратов (845)249-38-78	Ульяновск (8422)24-23-59
Владивосток (423)249-28-31	Киров (8332)68-02-04	Новосибирск (383)227-86-73	Севастополь (8692)22-31-93	Уфа (347)229-48-12
Волгоград (844)278-03-48	Краснодар (861)203-40-90	Омск (3812)21-46-40	Симферополь (3652)67-13-56	Хабаровск (4212)92-98-04
Вологда (8172)26-41-59	Красноярск (391)204-63-61	Орел (4862)44-53-42	Смоленск (4812)29-41-54	Челябинск (351)202-03-61
Воронеж (473)204-51-73	Курск (4712)77-13-04	Оренбург (3532)37-68-04	Сочи (862)225-72-31	Череповец (8202)49-02-64
Екатеринбург (343)384-55-89	Липецк (4742)52-20-81	Пенза (8412)22-31-16	Ставрополь (8652)20-65-13	Ярославль (4852)69-52-93
Иваново (4932)77-34-06	Киргизия (996)312-96-26-47	Россия (495)268-04-70	Казахстан (772)734-952-31	

# JML-Cable-18004 series millimeter microwave test cable assembly

**Features:** DC to 18GHz, multi-layer structure protection, with good stable amplitude, stable phase index, stable performance, reliable and durable.  
**Typical applications:** signal transmission in communication equipment, laboratory testing, production line testing and other areas of radio frequency microwave.

## Technical Parameters



### Structure

- 1.Inner Conductor: Silver Plated Copper
- 2.Insulation: LD-PTFE
- 3.Inner Shield: Silver Plated Copper Strip
- 4.Interlayer: LD-PTFE
- 5.Outer Shield: Silver Plated Copper Wire
- 6.Jacket: FEP
- 7.Inner Armor: Silver Plated Copper
- 8.Reinforced Braid: Silver Plated Copper Wire
9. Anti-torsion protection : PI
- 10.Outer Jacket: PTFE(Purple & Black)



Mechanical Characteristics						
Sheath outer diameter	7.65 mm	0.301 inch	Insertion/Withdrawal	>5000		
Weight	0.135kg/m		Operating Temperature	-55°C~+125°C		
Min Bending Radius	( Dynamic 50.0mm), (Static 25.0mm)		Armor compressive	180N/25mm		
Electrical Characteristics						
VSWR Max	Connector	3GHz	6GHz	18GHz	Impedance	50 ohms
	SMA	1.10:1	1.15:1	1.25:1	Velocity of Propagation	83%
	N	1.10:1	1.15:1	1.25:1	Screening Effectiveness	>90 dB
	TNC	1.10:1	1.15:1	1.30:1	Amplitude Change VS Bending	≤±0.03dB@18GHz
Capacitance	24.3pf/ft=80pf/m			Phase Change VS Bending	≤±2.4° @18GHz	
Cable attenuation and power						
	Attenuation(25°C)			Power handling(25°C, Sea Level, Cable)		
Frequency (MHz)	dB/100ft		dB/100m		Watts	
300	4.99		16.4		1519	
500	6.49		21.3		1171	
1000	9.27		30.4		821	
3000	16.40		53.8		464	
6000	23.65		77.6		321	
10000	31.15		102.2		244	
12000	34.69		113.8		221	
18000	43.07		141.3		177	
26500	53.52		175.6		142	

Архангельск (8182)63-90-72  
Астана (7172)727-132  
Астрахань (8512)99-46-04  
Барнаул (3852)73-04-60  
Белгород (4722)40-23-64  
Брянск (4832)59-03-52  
Владивосток (423)249-28-31  
Волгоград (844)278-03-48  
Вологда (8172)26-41-59  
Воронеж (473)204-51-73  
Екатеринбург (343)384-55-89  
Иваново (4932)77-34-06

Ижевск (3412)26-03-58  
Иркутск (395)279-98-46  
Казань (843)206-01-48  
Калининград (4012)72-03-81  
Калуга (4842)92-23-67  
Кемерово (3842)65-04-62  
Киров (8332)68-02-04  
Краснодар (861)203-40-90  
Красноярск (391)204-63-61  
Курск (4712)77-13-04  
Липецк (4742)52-20-81  
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13  
Москва (495)268-04-70  
Мурманск (8152)59-64-93  
Набережные Челны (8552)20-53-41  
Нижний Новгород (831)429-08-12  
Новокузнецк (3843)20-46-81  
Новосибирск (383)227-86-73  
Омск (3812)21-46-40  
Орел (4862)44-53-42  
Оренбург (3532)37-68-04  
Пенза (8412)22-31-16  
Россия (495)268-04-70

Пермь (342)205-81-47  
Ростов-на-Дону (863)308-18-15  
Рязань (4912)46-61-64  
Самара (846)206-03-16  
Санкт-Петербург (812)309-46-40  
Саратов (845)249-38-78  
Севастополь (8692)22-31-93  
Симферополь (3652)67-13-56  
Смоленск (4812)29-41-54  
Сочи (862)225-72-31  
Ставрополь (8652)20-65-13  
Казахстан (772)734-952-31

Сургут (3462)77-98-35  
Тверь (4822)63-31-35  
Томск (3822)98-41-53  
Тула (4872)74-02-29  
Тюмень (3452)66-21-18  
Ульяновск (8422)24-23-59  
Уфа (347)229-48-12  
Хабаровск (4212)92-98-04  
Челябинск (351)202-03-61  
Череповец (8202)49-02-64  
Ярославль (4852)69-52-93