

Кабели коаксиальные POMING JML-18007

Технические характеристики

Архангельск (8182)63-90-72	Ижевск (3412)26-03-58	Магнитогорск (3519)55-03-13	Пермь (342)205-81-47	Сургут (3462)77-98-35
Астана (7172)727-132	Иркутск (395)279-98-46	Москва (495)268-04-70	Ростов-на-Дону (863)308-18-15	Тверь (4822)63-31-35
Астрахань (8512)99-46-04	Казань (843)206-01-48	Мурманск (8152)59-64-93	Рязань (4912)46-61-64	Томск (3822)98-41-53
Барнаул (3852)73-04-60	Калининград (4012)72-03-81	Набережные Челны (8552)20-53-41	Самара (846)206-03-16	Тула (4872)74-02-29
Белгород (4722)40-23-64	Калуга (4842)92-23-67	Нижний Новгород (831)429-08-12	Санкт-Петербург (812)309-46-40	Тюмень (3452)66-21-18
Брянск (4832)59-03-52	Кемерово (3842)65-04-62	Новокузнецк (3843)20-46-81	Саратов (845)249-38-78	Ульяновск (8422)24-23-59
Владивосток (423)249-28-31	Киров (8332)68-02-04	Новосибирск (383)227-86-73	Севастополь (8692)22-31-93	Уфа (347)229-48-12
Волгоград (844)278-03-48	Краснодар (861)203-40-90	Омск (3812)21-46-40	Симферополь (3652)67-13-56	Хабаровск (4212)92-98-04
Вологда (8172)26-41-59	Красноярск (391)204-63-61	Орел (4862)44-53-42	Смоленск (4812)29-41-54	Челябинск (351)202-03-61
Воронеж (473)204-51-73	Курск (4712)77-13-04	Оренбург (3532)37-68-04	Сочи (862)225-72-31	Череповец (8202)49-02-64
Екатеринбург (343)384-55-89	Липецк (4742)52-20-81	Пенза (8412)22-31-16	Ставрополь (8652)20-65-13	Ярославль (4852)69-52-93
Иваново (4932)77-34-06	Киргизия (996)312-96-26-47	Россия (495)268-04-70	Казахстан (772)734-952-31	

JML-Cable-18007 series millimeter microwave test cable assembly

Features: DC to 26.5GHz, multi-layer structure protection, good stable amplitude, stable phase index, stable performance, reliable and durable.

Typical applications: signal transmission in communication equipment, laboratory testing, production line testing and other areas of radio frequency microwave.

Technical Parameters



Structure

- 1.Inner Conductor:** Silver Plated Copper
- 2.Insulation:** LD-PTFE
- 3.Inner Shield:** Silver Plated Copper Strip
- 4.Interlayer:** LD-PTFE
- 5.Outer Shield:** Silver Plated Copper Wire
- 6.Jacket:** FEP
- 7.Inner Armor:** Silver Plated Copper
- 8.Reinforced Braid:** Silver Plated Copper Wire
- 9. Anti-torsion protection :** PI
- 10.Outer Jacket:** PTFE(Purple & Black)



Mechanical Characteristics						
Sheath outer diameter	7.2 mm	0.283 inch	Insertion/Withdrawal	>5000		
Weight	0.5kg/m		Operating Temperature	-55°C ~+125°C		
Min Bending Radius	(Dynamic 46.0mm), (Static 18.0mm)		Armor compressive	160N/25mm		
Electrical Characteristics						
VSWR Max	Connector	6GHz	18GHz	26.5GHz	Impedance	50 ohms
	SMA/3.5mm	1.15:1	1.25:1	1.30:1	Velocity of Propagation	76%
	N	1.15:1	1.25:1	---	Screening Effectiveness	>90 dB
	TNC	1.15:1	1.30:1	---	Amplitude Change VS Bending	≤±0.03dB@26.5GHz
Capacitance	27pf/ft=88pf/m			Phase Change VS Bending	≤±2.7° @26.5GHz	
Cable attenuation and power						
	Attenuation (25°C)			Power handling(25°C, Sea Level,Cable)		
Frequency (MHz)	dB/100ft		dB/100m		Watts	
300	6.25		20.5		927	
500	8.08		26.5		717	
1000	11.46		37.6		505	
3000	19.99		65.6		289	
6000	28.53		93.6		203	
10000	37.12		121.8		156	
12000	41.27		135.4		137	
18000	50.41		165.4		115	
26500	61.81		202.8		94	

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93