

Кабели коаксиальные POMING JML-18008

Технические характеристики


Архангельск (8182)63-90-72	Ижевск (3412)26-03-58	Магнитогорск (3519)55-03-13	Пермь (342)205-81-47	Сургут (3462)77-98-35
Астана (7172)727-132	Иркутск (395)279-98-46	Москва (495)268-04-70	Ростов-на-Дону (863)308-18-15	Тверь (4822)63-31-35
Астрахань (8512)99-46-04	Казань (843)206-01-48	Мурманск (8152)59-64-93	Рязань (4912)46-61-64	Томск (3822)98-41-53
Барнаул (3852)73-04-60	Калининград (4012)72-03-81	Набережные Челны (8552)20-53-41	Самара (846)206-03-16	Тула (4872)74-02-29
Белгород (4722)40-23-64	Калуга (4842)92-23-67	Нижний Новгород (831)429-08-12	Санкт-Петербург (812)309-46-40	Тюмень (3452)66-21-18
Брянск (4832)59-03-52	Кемерово (3842)65-04-62	Новокузнецк (3843)20-46-81	Саратов (845)249-38-78	Ульяновск (8422)24-23-59
Владивосток (423)249-28-31	Киров (8332)68-02-04	Новосибирск (383)227-86-73	Севастополь (8692)22-31-93	Уфа (347)229-48-12
Волгоград (844)278-03-48	Краснодар (861)203-40-90	Омск (3812)21-46-40	Симферополь (3652)67-13-56	Хабаровск (4212)92-98-04
Вологда (8172)26-41-59	Красноярск (391)204-63-61	Орел (4862)44-53-42	Смоленск (4812)29-41-54	Челябинск (351)202-03-61
Воронеж (473)204-51-73	Курск (4712)77-13-04	Оренбург (3532)37-68-04	Сочи (862)225-72-31	Череповец (8202)49-02-64
Екатеринбург (343)384-55-89	Липецк (4742)52-20-81	Пенза (8412)22-31-16	Ставрополь (8652)20-65-13	Ярославль (4852)69-52-93
Иваново (4932)77-34-06	Киргизия (996)312-96-26-47	Россия (495)268-04-70	Казахстан (772)734-952-31	

JML-Cable-18008 series millimeter microwave test cable assembly

Features: frequency coverage DC to 40GHz, good stability in amplitude and phase, stable performance, reliable and durable MMW test cable assembly.

Typical applications: signal transmission in communication equipment, laboratory testing, production line testing and other areas of radio frequency microwave.

Technical Parameters



Structure

Inner Conductor: Silver Plated Copper

Insulation: LD-PTFE

Inner Shield: Silver Plated Copper Strip

Interlayer: LD-PTFE

Outer Shield: Silver Plated Copper Wire

Jacket: FEP



Mechanical Characteristics				
Dimension	mm	inch		
Inner Conductor	0.92	0.036		
Insulation	2.50	0.098		
Inner Shield	2.66	0.105		
Interlayer	2.95	0.116		
Outer Shield	3.11	0.122		
Jacket	3.80	0.150		
Weight	0.033kg/m			
Min Bending Radius	(Dynamic 38.0mm), (Static 14.4mm)			
Insertion/Withdrawal	>5000			
Operating Temperature	-55°C~+165°C			
Electrical Characteristics				
VSWR Max		18GHz	26.5GHz	40GHz
	2.92 mm	1.25:1	1.30:1	1.30:1
	2.4 mm	1.25:1	1.30:1	1.30:1
Impedance	50 ohms			
Velocity of Propagation	76%			
Screening Effectiveness	>90 dB			
Amplitude Change VS Bending	$\leq \pm 0.04\text{dB}@40\text{GHz}$			
Phase Change VS Bending	$\leq \pm 4^\circ @40\text{GHz}$			
Attenuation (25°C)				
Frequency (MHz)	dB/100ft	dB/100m		
1000	11.4	37.5		
3000	20.0	65.7		
6000	28.6	93.8		
10000	37.3	122.4		
12000	41.4	135.8		
18000	50.8	166.7		
26500	62.4	204.8		
40000	77.7	254.8		
Power handling (25°C, Sea Level, Cable)				
Frequency (MHz)	Watts			
1000	509			
3000	291			
6000	203			
10000	156			
12000	141			
18000	115			
26500	93			
40000	75			

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93