

Кабели коаксиальные POMING JML-18010

Технические характеристики

Архангельск (8182)63-90-72	Ижевск (3412)26-03-58	Магнитогорск (3519)55-03-13	Пермь (342)205-81-47	Сургут (3462)77-98-35
Астана (7172)727-132	Иркутск (395)279-98-46	Москва (495)268-04-70	Ростов-на-Дону (863)308-18-15	Тверь (4822)63-31-35
Астрахань (8512)99-46-04	Казань (843)206-01-48	Мурманск (8152)59-64-93	Рязань (4912)46-61-64	Томск (3822)98-41-53
Барнаул (3852)73-04-60	Калининград (4012)72-03-81	Набережные Челны (8552)20-53-41	Самара (846)206-03-16	Тула (4872)74-02-29
Белгород (4722)40-23-64	Калуга (4842)92-23-67	Нижний Новгород (831)429-08-12	Санкт-Петербург (812)309-46-40	Тюмень (3452)66-21-18
Брянск (4832)59-03-52	Кемерово (3842)65-04-62	Новокузнецк (3843)20-46-81	Саратов (845)249-38-78	Ульяновск (8422)24-23-59
Владивосток (423)249-28-31	Киров (8332)68-02-04	Новосибирск (383)227-86-73	Севастополь (8692)22-31-93	Уфа (347)229-48-12
Волгоград (844)278-03-48	Краснодар (861)203-40-90	Омск (3812)21-46-40	Симферополь (3652)67-13-56	Хабаровск (4212)92-98-04
Вологда (8172)26-41-59	Красноярск (391)204-63-61	Орел (4862)44-53-42	Смоленск (4812)29-41-54	Челябинск (351)202-03-61
Воронеж (473)204-51-73	Курск (4712)77-13-04	Оренбург (3532)37-68-04	Сочи (862)225-72-31	Череповец (8202)49-02-64
Екатеринбург (343)384-55-89	Липецк (4742)52-20-81	Пенза (8412)22-31-16	Ставрополь (8652)20-65-13	Ярославль (4852)69-52-93
Иваново (4932)77-34-06	Киргизия (996)312-96-26-47	Россия (495)268-04-70	Казахстан (772)734-952-31	

JML-Cable-18010 series millimeter microwave test cable assembly

Features: DC to 50GHz, multi-layer structure protection, with good stable amplitude, stable phase index, stable performance, reliable and durable.

Typical applications: signal transmission in communication equipment, laboratory testing, production line testing and other areas of radio frequency microwave.

Technical Parameters



Structure

- 1.Inner Conductor: Silver Plated Copper
- 2.Insulation: LD-PTFE
- 3.Inner Shield: Silver Plated Copper Strip
- 4.Interlayer: LD-PTFE
- 5.Outer Shield: Silver Plated Copper Wire
- 6.Jacket: FEP
- 7.Inner Armor: Silver Plated Copper
- 8.Reinforced Braid: Silver Plated Copper Wire
9. Anti-torsion protection : PI
- 10.Outer Jacket: PTFE(Purple & Black)



Mechanical Characteristics							
Sheath outer diameter	5.80 mm	0.228 inch		Insertion/Withdrawal	>5000		
Weight	0.042kg/m			Operating Temperature	-55°C~+125°C		
Min Bending Radius	36.0mm			Armor compressive	100N/25mm		
Electrical Characteristics							
VSWR Max	Connector	18GHz	26.5GHz	40GHz	50GHz	Medium pressure	500V, DC
	2.92mm	1.25:1	1.30:1	1.30	--	Velocity of Propagation	76%
	2.4mm	1.25:1	1.30:1	1.30	1.35	Screening Effectiveness	>90 dB
Impedance	50 ohms				Amplitude Change VS Bending	±0.05dB@50GHz	
Capacitance	27pf/ft=88pf/m				Phase Change VS Bending	≤±5° @50GHz	
Cable attenuation and power							
	Attenuation (25°C)			Power handling(25°C, Sea Level, Cable)			
Frequency (MHz)	dB/100ft		dB/100m		Watts		
300	13.4		23.9		580		
500	23.3		30.9		420		
1000	33.2		43.8		250		
3000	43.1		76.4		140		
6000	48.2		108.8		130		
12000	58.5		158.1		80		
18000	71.6		191.8		72		
26500	88.9		234.8		66		
40000	13.4		291.7		60		
50000	23.3		328.5		56		

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93